



CE RoHS

With our line of No Touch exit button you no longer have to physically push a button to exit. All you have to do is wave your hand and the door will open. This No Touch exit button also includes a delay feature to up to 22 seconds.

Door Release Exit Buttons are the most common part in Access Control systems. They are often used in all types of applications such as in Offices, Banks, Gas Stations, Department Stores and much more.

The VISIONIS Request-to-Exit Buttons may be connected to the request-to-exit input of any access control device or directly connected to an electromagnetic lock or Electric strike Device.

Model No.	VIS-7013
Contact Rating	12-24V, 3A
Output Contact	NO/NC/COM
Detection Range	5-15cm (1.96 - 5.90in.), Adjustable
Power	12VDC or 24VDC
LED Color	Blue (Stand by Mode), Green (Active/Open Mode)
Time Delay	0.5~22s
Panel	4mm (0.15) Thick Aluminium Alloy (CNC)
Suitable for	Hollow Door
Mechanical Life	100.000 tests
Operating Temperature	-20°C~+55°C (14°F-131°F)
Operating Humidity	0-95% (relative humidity)
Weight	0.105kg
Dimensions	115L × 70W × 25H mm - 4.52L x 2.75W x 0.98H in.



Disclaimer: VISIONIS reserve the right to go ahead with any modifications of models or features or price without forewarning. All the information and specifications stated in this document are current at the time of publication. Attention: We are not responsible for the improper installation of this product. If you are not handy with electrical equipment you should contact a professional electrician. You will also need to check with your local Fire authority to see if you need anything else to comply with local Fire Codes. We are not responsible for any damage or fees that can occur.



sales@visionistech.com



www.visionistech.com